


# OM20 Quick Installation Guide



## Accessories




Main Body



Power Adapter



CAT5 Ethernet Cable



Grounding Cable



Rubber Footpads




Installation Guide



19-inch Rack Mounting Kits  
(Optional)

## Connection

\*The illustration below takes OM20-2S/2 as an example.



Front panel indicators:

Indicator	Status	Device
FXO	Yellow	Starting
FXS	Green	Starting
PWR	Steady Green	Successful startup


## Analog Phone

- #00 Obtain phone number
- ## Obtain device IP address

To obtain the installation video on YouTube, enter "New Rock OM20" in the search box.

## New Rock NRP Series IP Phone

1. After connection and powered on, input PIN for the extension and click **OK**.



2. When **The PIN is right!** prompts, click **OK** to reboot to make the configuration effective.
3. The extension number will display after a reboot.

Extension	PIN
212	447669
213	824005
214	116008
215	467464
216	050026
217	757877
218	024096
219	132968
220	399357
221	371225

An IP extension registered using the factory default PIN is only allowed to call other extensions.

To recover the call permission, go to Extensions > IP to modify the PIN and password.

## Log into OM20

1. Dial ## to obtain device IP address by an analog phone.
2. Ensure your PC and the device is on the same network segment.
3. Enter the device IP address in the browser address bar. (Default: 192.168.2.218).  
Enter initial password **admin** to log in to the device.

Be sure to change the password after the first login. If internet explorer prompts for risk action, select "allow".  
\* For OM20-4FXO, the device IP address can be obtained via "Finder" software. You can download it from Products>Application Software>Finder on our website.

## Mobile Extension (WeWei App)

1. Scan the QR code below to download and install WeWei.



- \* You can also obtain the QR code by moving cursor on icon  from OM20 login interface.
2. Run the software and enter PIN to register the mobile extension.  
The extension number displays on the upper left of WeWei interface if the extension is registered successfully.

## NeeHau Business Phone Assistant

1. Click icon  on OM20 login interface to download and install NeeHau.
2. Run the software and login as:
  - User: Enter the PIN of registered extension. Click **Log in** to finish the bundling of extension.
  - Administrator: Enter username **admin** and password **admin54321**. Be sure to change the password after the first login.

## Static IP Address

It is recommended to assign a static IP address for your OM20.


**Method 1:** On analog phone, dial \*90 and configure your network parameters as the following example:

192\*168\*2\*218#255\*255\*0\*0#192\*168\*2\*1#0#

IP address
Subnet mask
Default gateway

The configuration takes effect after a reboot.

**Method 2:** On OM20 interface, go to **Basic > Network** page to select **Static IP** and configure the network parameters.



## Notes

1. Do not connect the POTS telephone line and PBX phone line to FXS ports.
2. To restore the OM20 to factory default, press the RST for more than 3 seconds.
3. Be sure to use the power adapter supplied with OM20.